

# Product Environmental Profile

## Exxact USB power supply






## General information

Representative product	Exxact USB power supply - WDE002928
Description of the product	The function of the socket is to allow users to connect and disconnect the plug of an electrical load or the source of a signal from a network:Electronic: Loudspeaker socket, USB socket.
Functional unit	Make available during 20 years ,2 USB 2.0 port 5 V DC, maximum load current: 2.1 A



## Constituent materials

Reference product mass 98.1 g including the product, its packaging and additional elements and accessories



Plastics	29.1%
Metals	20.4%
Others	50.4%



## Substance assessment

Products of this range are designed in conformity with the requirements of the RoHS directive (European Directive 2011/65/EU of 8 June 2011) and do not contain, or only contain in the authorised proportions, lead, mercury, cadmium, hexavalent chromium or flame retardants (polybrominated biphenyls - PBB, polybrominated diphenyl ethers - PBDE) as mentioned in the Directive

As the products of the range are designed in accordance with the RoHS Directive (European Directive 2002/95/EC of 27 January 2003), they can be incorporated without any restriction in an assembly or an installation subject to this Directive.

Details of ROHS and REACH substances information are available on the Schneider-Electric Green Premium website

<http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page>



## Additional environmental information

The Exxact USB power supply presents the following relevant environmental aspects


<b>Manufacturing</b>	Manufactured at a Schneider Electric production site ISO14001 certified
<b>Distribution</b>	Weight and volume of the packaging optimized, based on the European Union's packaging directive Packaging weight is 21.1 g, consisting of cardboard (75%), Paper(25%)
<b>Installation</b>	This product does not require any special components during installation
<b>Use</b>	The product does not require special maintenance operations.
<b>End of life</b>	End of life optimized to decrease the amount of waste and allow recovery of the product components and materials  This product contains electronic card (22.85g) that should be separated from the stream of waste so as to optimize end-of-life treatment.  <a href="http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page">http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page</a>  Recyclability potential: <b>33%</b> Based on "ECO'DEEE recyclability and recoverability calculation method" (version V1, 20 Sep. 2008 presented to the French Agency for Environment and Energy Management: ADEME).



## Environmental impacts

<b>Reference life time</b>	20 years			
<b>Product category</b>	USB socket			
<b>Installation elements</b>	No special installation components need during installation phase, but transport of packaging to disposal, and disposal of packaging accounted for during installation			
<b>Use scenario</b>	Load rate: 100 % of the rated current according to the USB standards Load rate: 30 % de the RLT			
<b>Geographical representativeness</b>	Europe			
<b>Technological representativeness</b>	The function of the socket is to allow users to connect and disconnect the plug of an electrical load or the source of a signal from a network: Electronic: Loudspeaker socket, USB socket.			
<b>Energy model used</b>	<b>Manufacturing</b>	<b>Installation</b>	<b>Use</b>	<b>End of life</b>
	Energy model used: Germany - Wiehl	Electricity grid mix; AC; consumption mix, at consumer; < 1kV; EU-27	Electricity grid mix; AC; consumption mix, at consumer; < 1kV; EU-27	Electricity grid mix; AC; consumption mix, at consumer; < 1kV; EU-27

Compulsory indicators		Exxact USB power supply - WDE002928					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to mineral resources depletion	kg Sb eq	7.57E-05	6.75E-05	0*	0*	8.14E-06	0*
Contribution to the soil and water acidification	kg SO <sub>2</sub> eq	3.95E-01	3.61E-03	5.78E-05	0*	3.91E-01	0*
Contribution to water eutrophication	kg PO <sub>4</sub> <sup>3-</sup> eq	2.53E-02	1.69E-03	1.33E-05	3.59E-06	2.36E-02	6.17E-06
Contribution to global warming	kg CO <sub>2</sub> eq	9.66E+01	2.80E+00	1.27E-02	0*	9.37E+01	1.04E-02
Contribution to ozone layer depletion	kg CFC11 eq	6.47E-06	3.66E-07	0*	0*	6.11E-06	0*
Contribution to photochemical oxidation	kg C <sub>2</sub> H <sub>4</sub> eq	2.19E-02	4.48E-04	4.12E-06	0*	2.15E-02	2.48E-06
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Net use of freshwater	m <sup>3</sup>	3.40E+02	0*	0*	0*	3.40E+02	0*
Total Primary Energy	MJ	1.91E+03	3.45E+01	0*	0*	1.87E+03	0*



Optional indicators		Exxact USB power supply - WDE002928					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to fossil resources depletion	MJ	1.10E+03	3.23E+01	1.78E-01	0*	1.06E+03	0*
Contribution to air pollution	m³	4.29E+03	2.57E+02	5.38E-01	0*	4.03E+03	8.33E-01
Contribution to water pollution	m³	4.17E+03	2.96E+02	2.08E+00	0*	3.87E+03	9.55E-01
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Use of secondary material	kg	2.34E-04	2.34E-04	0*	0*	0*	0*
Total use of renewable primary energy resources	MJ	2.39E+02	1.38E+00	0*	0*	2.38E+02	0*
Total use of non-renewable primary energy resources	MJ	1.67E+03	3.31E+01	1.79E-01	0*	1.63E+03	0*
Use of renewable primary energy excluding renewable primary energy used as raw material	MJ	2.39E+02	9.61E-01	0*	0*	2.38E+02	0*
Use of renewable primary energy resources used as raw material	MJ	4.20E-01	4.20E-01	0*	0*	0*	0*
Use of non renewable primary energy excluding non renewable primary energy used as raw material	MJ	1.67E+03	3.16E+01	1.79E-01	0*	1.63E+03	0*
Use of non renewable primary energy resources used as raw material	MJ	1.49E+00	1.49E+00	0*	0*	0*	0*
Use of non renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Waste categories	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Hazardous waste disposed	kg	2.60E+00	2.42E+00	0*	0*	4.89E-02	1.32E-01
Non hazardous waste disposed	kg	3.50E+02	7.44E-01	0*	0*	3.49E+02	0*
Radioactive waste disposed	kg	2.34E-01	6.78E-04	0*	0*	2.33E-01	0*
Other environmental information	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Materials for recycling	kg	4.88E-02	6.84E-03	0*	1.60E-02	0*	2.60E-02
Components for reuse	kg	0.00E+00	0*	0*	0*	0*	0*
Materials for energy recovery	kg	1.12E-03	1.42E-04	0*	0*	0*	9.75E-04
Exported Energy	MJ	2.92E-03	0*	0*	2.92E-03	0*	0*

\* represents less than 0.01% of the total life cycle of the reference flow

Life cycle assessment performed with EIME version EIME v5.7.0.2, database version 2016-11 in compliance with ISO14044.

The use phase is the life cycle phase which has the greatest impact on the majority of environmental indicators (based on compulsory indicators).

Please note that the values given above are only valid within the context specified and cannot be used directly to draw up the environmental assessment of an installation.

Registration number :	SCHN-00334-V01.01-EN	Drafting rules	PCR-ed3-EN-2015 04 02
Verifier accreditation N°	VH25	Supplemented by	PSR-0005-ed2-EN-2016 03 29
Date of issue	05/2018	Information and reference documents	<a href="http://www.pep-ecopassport.org">www.pep-ecopassport.org</a>
		Validity period	5 years
Independent verification of the declaration and data, in compliance with ISO 14025 : 2010			
Internal	External	X	
The PCR review was conducted by a panel of experts chaired by Philippe Osset (SOLINNEN)			
PEP are compliant with XP C08-100-1 :2014			
The elements of the present PEP cannot be compared with elements from another program.			
Document in compliance with ISO 14025 : 2010 « Environmental labels and declarations. Type III environmental declarations »			



Schneider Electric Industries SAS

Country Customer Care Center  
<http://www.schneider-electric.com/contact>

35, rue Joseph Monier  
 CS 30323  
 F- 92506 Rueil Malmaison Cedex  
 RCS Nanterre 954 503 439  
 Capital social 896 313 776 €

[www.schneider-electric.com](http://www.schneider-electric.com)

Published by Schneider Electric

SCHN-00334-V01.01-EN

© 2017 - Schneider Electric – All rights reserved

05/2018